



بازرگانی تاج

Model	KDF 11000 XE - 3D	
Rated Frequency [Hz]	50	
Rated Voltage [V]	220	380
Rated Output Power [KVA]	8	10
Max Output Power [KVA]	8.5	10.6
Phase Number	Single	Three
Power Factor Cos Φ	1	0.8
Fuel Tank Capacity [L]	12.5	
Frame Type	35 * 35mm	Square tube frame
Engine Model	KD1100F	
Starting System	Electric starter (only)	
Engine Type	1-Cylinder ,4-Stroke ,Air-cooled, Vertical	
Broke * Stroke [mm]	100 * 85	
Displacement [L]	0.667	
Compression Ratio	20:1	
Rated Rotation Speed [rpm]	3000	
Oil Capacity [L]	2	
Fuel Consumption [g/kwh]	275	
Fuel Consumption (Lit/H)	3.3	
Optional Standard	ATS / Digital Smart Panel / Wheel and handle	
Noise (db) (@7m)	88	
Overall Dimension [mm](L*W*H)	780*585*705	
Net Weight [kg]	160	

شرکت بازرگانی تاج

شماره تماس: 09197660259 - 02136908538

09127037109 - 09197660249 - 02136057230

آدرس موتور برق شاپ

تهران، خیابان سعدی جنوبی، کوچه فوآنساری، ساختمان